



GUANGZHOU JIUAN MECHANICAL AND ELECTRICAL CO.,LTD

Email:manager@jiuanguarder.com Web:www.jiuanguarder.com Tel:0086 13751743050

Add: NO.1 DongXingXiang,TanBuTown,HuaDuDistrict,Guangzhou,China

广州市花都区炭步镇三联村袁竹坳东兴巷1号



Technical Specifications

Genset Model	Engine Model	Frequency	Speed	Engine Power(KW)			Genset Power (KW)			Genset Power (KVA)		
				Continuous	Prime	Standby	Continuous	Prime	Standby	Continuous	Prime	Standby
CDD22KVA	BFM3 G3	50Hz	1500rpm	18	20	22	14.4	16	17.6	18	20	22
CDD27KVA	BFM3 G4	50Hz	1500rpm	22	25	27	17.6	20	21.6	22	25	27
CDD33KVA	BFM3T G1	50Hz	1500rpm	27	30	33	22.4	24	26.4	28	30	33
CDD44KVA	BFM3T G2	50Hz	1500rpm	36	40	44	28.8	32	35.2	36	40	44
CDD55KVA	BFM3C G1	50Hz	1500rpm	40	44	50	36	40	44	45	50	55
CDD65KVA	BF4M2012	50Hz	1500rpm	51	54	60	44	48	52	55	60	65
CDD80KVA	BF4M2012C G1	50Hz	1500rpm	64	71	75	56	60	64	70	75	80
CDD100KVA	BF4M2012C G2	50Hz	1500rpm	78	85	93	65.6	72	80	82	90	100
CDD110KVA	BF4M1013EC G1	50Hz	1500rpm	92	97	102	72	80	88	90	100	110
CDD125KVA	BF4M1013EC G2	50Hz	1500rpm	96	105	116	80	89.6	100	100	112	125
CDD145KVA	BF4M1013FC	50Hz	1500rpm	106	117	129	96	104	116	120	130	145
CDD175KVA	BF6M1013EC G1	50Hz	1500rpm	139	146	153	120	128	140	150	160	175
CDD200KVA	BF6M1013EC G2	50Hz	1500rpm	150	160	175	132	144	160	165	180	200
CDD210KVA	BF6M1013FCG2	50Hz	1500rpm	151	166	183	132	150.4	168	165	188	210
CDD220KVA	BF6M1013FCG3	50Hz	1500rpm	166	183	201	144	160	176	180	200	220
CDD275KVA	TCD8.0	50Hz	1500rpm	207	225	250	184	200	220	230	250	275
CDD330KVA	TCD8.7	50Hz	1500rpm	240	265	290	224	240	264	280	300	330
CDD350KVA	TCD12.1 G1	50Hz	1500rpm	268	290	330	240	260	280	300	325	350
CDD400KVA	TCD12.1 G2	50Hz	1500rpm	310	330	360	280	300	320	350	375	400
CDD500KVA	TCD13 G1	50Hz	1500rpm	365	395	435	336	360	400	420	450	500
CDD550KVA	TCD13 G2	50Hz	1500rpm	405	440	470	360	400	440	450	500	550
CDD688KVA	D17	50Hz	1500rpm	510	565	615	448	500	550.4	560	625	688

Genset Model	Engine Model	Frequency	Speed	Engine Power(KW)			Genset Power (KW)			Genset Power (KVA)		
				Continuous	Prime	Standby	Continuous	Prime	Standby	Continuous	Prime	Standby
CDD28KVA	BFM3 G3	60Hz	1800rpm	23	25	28	18	20	22.4	22.5	25	28
CDD32KVA	BFM3 G4	60Hz	1800rpm	26	29	32	21.6	24	25.6	27	30	32
CDD38KVA	BFM3T G1	60Hz	1800rpm	31	35	38	25.6	28	30.4	32	35	38
CDD53KVA	BFM3T G2	60Hz	1800rpm	42	45	50	36	38	42.4	45	47.5	53
CDD65KVA	BFM3C G1	60Hz	1800rpm	50	55	60	44	48	52	55	60	65
CDD75KVA	BF4M2012	60Hz	1800rpm	60	63	70	52	56	60	65	70	75
CDD90KVA	BF4M2012C G1	60Hz	1800rpm	75	79	88	60	65.6	72	75	82	90
CDD110KVA	BF4M2012C G2	60Hz	1800rpm	90	99	108	72	80	88	90	100	110
CDD120KVA	BF4M1013EC G1	60Hz	1800rpm	100	105	110	80	89.6	96	100	112	120
CDD140KVA	BF4M1013EC G2	60Hz	1800rpm	105	115	125	89.6	100	112	112	125	140
CDD150KVA	BF4M1013FC	60Hz	1800rpm	112	124	136	104	110	120	130	137.5	150
CDD180KVA	BF6M1013EC G1	60Hz	1800rpm	148	155	163	120	134.4	144	150	168	180
CDD215KVA	BF6M1013EC G2	60Hz	1800rpm	165	181	197	144	160	172	180	200	215
CDD230KVA	BF6M1013FC G2	60Hz	1800rpm	169	186	204	144	168	184	180	210	230
CDD245KVA	BF6M1013FC G3	60Hz	1800rpm	186	204	225	160	176	196	200	220	245
CDD285KVA	TCD8.0	60Hz	1800rpm	223	245	270	192	212	228	240	265	285
CDD350KVA	TCD8.7	60Hz	1800rpm	260	290	320	240	256	280	300	320	350
CDD413KVA	TCD12.1 G1	60Hz	1800rpm	310	335	365	272	300	330.4	340	375	413
CDD438KVA	TCD12.1 G2	60Hz	1800rpm	320	353	385	288	320	350.4	360	400	438
CDD500KVA	TCD13 G1	60Hz	1800rpm	380	410	445	344	374.4	400	430	468	500
CDD555KVA	TCD13 G2	60Hz	1800rpm	410	445	485	376	400	444	470	500	555
CDD688KVA	D17	60Hz	1800rpm	510	565	615	448	500	550.4	560	625	688